

CHE-HDBTWP240K

## RS-232 Command

Baud Rate: 9600 , Data Bits: 8, Stop Bits: 1, Parity: None

Item	Command	Description	Example Response
1	s factory reset!	Return to factory reset setting	factory reset
2	r version!	Read current firmware version	Vx.xx
3	xyz!	Upgrade firmware	
4	s lock on!	Lock on the button control	lock on
5	s lock off!	Lock off the button control	lock off
6	r lock!	Read the button lock status	lock on or lock off
7	s auto switch on!	Enable auto switch function	auto switch on
8	s auto switch off!	Disable auto switch function	auto switch off
9	r auto switch!	Read auto switch function status	auto switch on or auto switch off
10	r source!	Read current input source	HDMI OR VGA
11	s source 1!	Switch HDMI input	HDMI
12	s source 2!	Switch VGA input	VGA